

X-VERTER 812



The X-Verter series UPS is an advanced Line-Interactive Uninterruptible Power System which produces pure sine wave power to your equipment; unlike the traditional off-line UPS (or Inverter), the series provides low harmonic sine wave output and very short transference when blackouts happen.

Features:

- * Inlet of city power.
- * AC Fuse.
- * Battery connector (12V DC).
- * RS-232 Interface (optional).
- * Outlet(s) (NEMA).
- * USB Port
- * Cooling Fan.
- * Holes for wall mounting.



Model
Capacity
INPUT
Voltage
Frequency
Current (110V/220V)
OUTPUT
Voltage
Frequency
Wave Form
Current (110V/220V)
Transfer time
Battery
Voltage
Level Ind.
Recharge current
Led / Alarm indication
Normal city power
Back up Mode
Abnormal Freq. of City power (Frequency > 65Hz or < 47Hz)
Abnormal Voltage of City power Too High / Low
Battery Replacement
Low Battery Alarm
Wrong Battery Alarm / Over load Alarm
Thermal Alarm / Short circuit
Load level indication
DC start / Alarm reset
Operation temp.
Operation humidity
Dimensions (L x H x W)
Shipping dim. (L x H x W)
Weight (N.W. / G.W.)

X-VERTER812 (Display by LCD or LED)
800VA (600W)
220/230/240V 1ø
Frequency
50Hz/60Hz Auto detect
220/230/240V 1ø or ±8% optional for wide input range.
50Hz or 60Hz ± 0.1Hz
Pure Sine Wave
7.7A / 3.9A
5 mS typical
Lead-Acid
User supplied 12 volts
YES
25A maximum
LED (Please Ref. to 5.2 for LCD display)
GRN
ORG
GRN
Blinking GRN
Blinking ORG
Blinking RED
YES
YES
0 – 40 °C
30-95% Non-Condensing
370x250x120mm
470x310x220mm
10/11kgs

CDP COLOMBIA colombia@cdpups.com CDP GUATEMALA guatemala@cdpups.com CDP PERÚ peru@cdpups.com

"Specifications subject to change without notice"

CDP USA usa@cdpups.com CDP ECUADOR ecuador@cdpups.com CDP CHINA china@cdpups.com CDP COSTA RICA costarica@cdpups.com CDP VENEZUELA venezuela@cdpups.com CDP HONG KONG hongkong@cdpups.com CDP MÉXICO mexico@cdpups.com

Check out our new online catalog.

www.cdpups.com